

Comdial Digitech - Changing time and date from attendant station:

1. Press the "ITCM" key.
2. Dial *#01.
3. Enter the date in YYMMDD format.
4. Enter 2 digits (00-23) for hour and 2 digits for minutes.
5. Press SPKR to end.

Comdial DSU/DSU II

- From extension 10, press "*#746*"
- Option One
 - Dial "01"
 - dial 00-99 for year
 - Dial 10-12 for month
 - Dial 1-31 for day
 - Dial 00-23 for hour
 - Dial 00-59 for minute.
- Option Two
 - Dial 00-23 for hour
 - Dial 00-59 for minute
 - Dial "#" to assign hours and minutes.
- Press speaker to exit.

Comdial DX-80

- Press "Feature" "#" "*" and enter your password (default is "#####").
- Press "Show" and "0814"
- Press "Save" and then "Show".
- The option to change the year appears. Press "Next" to skip. To change, press "Chg" then enter 2 digits for the year and then "Save" and "Next".
- The option to change the month appears. Press "Next" to skip. To change, press "Chg" then enter 2 digits for the month and then "Save" and "Next".
- The option to change the day appears. Press "Next" to skip. To change, press "Chg" then enter 2 digits for the date and then "Save" and "Next".
- The option to change the weekday appears. Press "Next" to skip. To change, press "Chg" until you see the day you want. Press "Save" and "Next".
- The option to change the hour appears. Press "Next" to skip. To change, press "Chg" then enter 2 digits for the hour in military format and then "Save" and "Next".
- The option to change the minutes appears. Press "Next" to skip. To change, press "Chg" then enter 2 digits for the minutes and then "Save".
- Press the "On/Off" button to exit the programming mode.

Comdial DXP

- Press "Intercom *#0*".
- Select "01".
- Enter date (MM:DD:YY).
- Enter time (HH:MM).
- Press "#" to end.
-

Adjusting the Comdial Digitech & Impact For Daylight Savings Time

Changing date & time on the Comdial Digitech & Impact

1. At Station 10 oir 12, Press ITCM button, Dial * # 0 1
2. Dial Two Digit Year
3. Dial Two Digit Month
4. Dial Two Digit Day
5. Dial Two Digit Hour
6. Dial Two Digit Minute
7. Press Monitor or Speaker Button to store.